

Technical Specifications TL-A70-40W

Features at a Glance

- Switchable 70V or 100V output
- Selectable 3 levels MIC input
- Controlled by buttons, IR and RS232
- 16 ID codes for RS232 identification



The TL-A70-40W is a compact-size amplifier that features alternative 70V or 100V output. It has 2 stereo inputs, 1 digital audio input and 1 MIC input. The TL-A70-40W can be controlled by button, IR, or RS232 command. It includes powerful functions, including ducking, EQ control, MIC mixer.

Specifications

I/O Connections	
Analog Inputs	Two(2) RCA jack, One(1) 3.5mm TRS jack
Digital Input	One(1) optical jack
MIC Input	One(1) 3-pin captive screw connector/3.81mm
IR Input	One(1) 3.5mm TRS Jack
RS232 Control	One(1) 3-pin captive screw connector/3.81mm
RS232 ID Selector	One(1) 16 ID codes for control
Button Control(Front Panel)	Five(5) buttons in total
MIC Signal Type Selector	One(1) 3-position slider switch
70V or 100V amplifier Output	One(1) 3-pin captive screw connector/3.81mm
DC 24V Power	One(1) Power connector with locking screw (5.5mm outside diameter, 2.1mm inside diameter)





Audio Performance	
Input Impedance	>10k Ω
Output Type	Constant voltage 70V or 100V
Maximum Rated Power Output	40 Watts
Frequency Response	120 Hz ~ 20 kHz
Common Mode Rejection Ratio (CMRR)	>70 dB at 20 Hz ~ 20 kHz
Signal to Noise Ratio (SNR)	80 dB (Max)
Total Harmonic Distortion + Noise (THD+N)	1% at 1 kHz; 0.3% at 20 kHz at Nominal Level
Voltage Gain	26 dB
Chassis and Environmental	
Enclosure	Painted aluminum
Dimensions (W x H x D)	130mm x 44mm x 144mm (5.12in x 1.73in x 5.67in)
Shipping Weight	1.10Kg(2.43bls)
Operating Temperature (Environment)	-10° ~ +40° C(+14° ~ +104° F)
Operating Temperature (Chassis)	45° C(113° F)
Operating Humidity (Environment)	10% ~ 90% Non-condensing
Storage Temperature (Environment)	-15° ~ +70° C(+5° ~ +158° F)
Storage Humidity (Environment)	10% ~ 90% Non-condensing
Power, ESD, Regulatory	
Maximum Power Consumption	45W
Power Supply	DC 24V at 2.5A
ESD Protection	15KV
Regulatory	CE, FCC
Other	
Standard Warranty	1 Year
Indicators	1 Power, 2 Input Select ,4 Signal select, 1 Up, 1 Down, 1 Mute
Included Items	Installation guide, Power adapter, Mounting ears(2 ea), Mounting screws(4 ea), RS232 cable, Plastic cushions (4 ea), Pluggable terminal black





Dimensional Drawings







